

Dimming Performance Results - Summary

LED Source Product Code	Driver Product Code	LED Type	Rated Power (W)	Control Type	Dimmer Switch Model	Performance Min-Typical (MAX)	Range % (no. of lamps)	Overall Rating
DB6-R999-3000K	DOMINO-140MA-DR-DIM	Engine + Driver	6	Trailing	DIGI-DM	1 - 12 (12)	10-100 (1-3) 15-100 (4-12)	Holy Grail
DB8-R999-3000K	DOMINO-180MA-DR-DIM	Engine + Driver	8	Trailing	DIGI-DM	1 - 12 (12)	10-100 (1-12)	Holy Grail
DB13-R999-3000K	DOMINO-300MA-DR-DIM	Engine + Driver	13	Trailing	DIGI-DM	1 - 12 (12)	10-100 (1-5) 15-100 (6-12)	Holy Grail
DB8-2700K-CRI98-18V-350MA	DOMINO-350MA-DR-DIM	Engine + Driver	8	Trailing	DIGI-DM	1-12 (12)	15-100 (1-12)	Holy Grail
MTG21-WH-2700K-CRI90	DOMINO-250MA-DR-DIM	Engine + Driver	10	Trailing	DIGI-DM	1-12 (12)	10-100 (1-4) 15-100 (5-12)	Holy Grail
TEMPUS-2-WH-3000K	DOMINO-140MA-DR-DIM	Engine + Driver	7	Trailing	DIGI-DM	2-12 (12)	15-100 (1-4) 20-100(5-12)	Holy Grail
TEMPUS-2-MINI-WH-3000K	DOMINO-140MA-DR-DIM	Engine + Driver	3	Trailing	DIGI-DM	2-12 (12)	15-100 (1-4) 20-100(5-12)	Holy Grail
PHILIPS WarmGlow Dimmable 8.5W 2200K-2700K	N/A	Lamp - E27	8.5	Trailing	DIGI-DM	1	10-100 (1)	Holy Grail
TDLEDFIL6W-2700K-D	N/A	Lamp - E27	9	Trailing	DIGI-DM	1-3	10-100 (1) 15-100 (2-3)	Holy Grail
LS3-7W-4000K-MKD2	N/A	Lamp - GU10	7	Leading	DIGI-DM	1-12	30-100 (1-12)	Acceptable
LS3-7W-4000K-MKE	N/A	Lamp - GU10	7	Leading	DIGI-DM	1-12	30-100 (1-12)	Acceptable
CR-5-5000K-D	N/A	Lamp - GU10	5	Leading	DIGI-DM	1-12	30-100 (1-12)	Acceptable
CR-4.5-4000K-D	N/A	Lamp - GU10	4.5	Leading	DIGI-DM	1-12	30-100 (1-12)	Acceptable
LS3-4000K-LD	N/A	Lamp - GU10	7	Leading	DIGI-DM	1-12	0-100 (1-12)	Holy Grail
LS3-7W-4000K-D	N/A	Lamp - GU10	7	Trailing	DIGI-DM	1-12	15-100 (1-12)	Holy Grail
LP3-7W-4000K-D	N/A	Lamp - GU10	7	Trailing	DIGI-DM	1-12	15-100 (1-12)	Holy Grail