

# Dimming Performance Test Results

## LED information

Model DB13-R999-3000K

Driver Product CodeDOMINO-300MA-DR-DIMBatch No.DRV - 17364 ENG - P185

**LED Type** Engine + Driver

Soft Start No
Rated Power (W) 13
Type LED
Control Type Trailing

#### **LED Image**



#### Switch / control information

Dimmer Switch Model DIGI-DM
PerformanceMin-Typical (MAX) 1 - 12 (12)

 Range% (no. of lamps)
 10-100 (1-5)15-100 (6-12)

 MinSet
 10%-15% see notes

 MaxSet
 Factory Default

Dimming set to Trailing

# Additional Image



## **Testing Environment**

 Voltage
 238

 F (Hz)
 50

 Room temp
 21

 Current Draw (Max)
 N/A

 PF at Max
 N/A

 Tester Initials
 JS

Date 20/10/2021

**Printed Date** 02/12/2021

Overall performance

Overall Rating Holy Grail

Diming Smoothness OK

Audible Noise on Dimmer No noise
Audible Noise on Driver No noise

Comments Smooth dimming and stable. >6 drivers, lowest dim level slight shimmer. Can be resolved by

trimming up 1 step.

Other Comments N/A

Other Reference DB13\_R999\_3000K DOMINO\_300MA\_DR\_DIM