

# Dimming Performance Test Results

## LED information

<b>Model</b>	TDLEDFIL6W-2700K-D
<b>Driver Product Code</b>	N/A
<b>Batch No.</b>	SOL19-021
<b>LED Type</b>	Lamp - E27
<b>Soft Start</b>	No
<b>Rated Power (W)</b>	9
<b>Type</b>	LED
<b>Control Type</b>	Trailing

## LED Image



## Switch / control information

<b>Dimmer Switch Model</b>	DIGI-DM
<b>PerformanceMin-Typical (MAX)</b>	1-3
<b>Range% (no. of lamps)</b>	10-100 (1)15-100 (2-3)
<b>MinSet</b>	Factory Default(1)see notes(2-3)
<b>MaxSet</b>	Factory Default
<b>Dimming set to</b>	Trailing

## Additional Image

## Testing Environment

<b>Voltage</b>	242
<b>F (Hz)</b>	50
<b>Room temp</b>	23
<b>Current Draw (Max)</b>	NA
<b>PF at Max</b>	N/A
<b>Tester Initials</b>	JS
<b>Date</b>	12/11/2021

**Printed Date** 02/12/2021

## Overall performance

<b>Overall Rating</b>	Holy Grail
<b>Diming Smoothness</b>	OK
<b>Audible Noise on Dimmer</b>	No noise
<b>Audible Noise on Driver</b>	No noise
<b>Comments</b>	Trim minimum to 10% higher for >1 lamps

**Other Comments** N/A

**Other Reference** TDLEDFIL6W\_2700K\_D N\_A